

QUICK REFERENCE GUIDE

Make a Call



Attendant	9
External number	0 + external number
Abbreviated number	2 + abbreviated number
Redial last-dialed external number	1 1
Avoiding receiving bips or intrusion	7 4 + external number
Sign-on/sign-off	7 5 + your terminal No. + password + C + No. to call
Automatic call-back	1 (or R + 1)
Intrusion	3 (or R + 3)
Voice message	3 (or R + 3)
Voice message to a group	Dial number of the group

Answer a call



Call pick-up	1 3 + number of ringing extension
Call pick-up in a group	1 4
General ringing call pick-up	1 5
Opening the door phone	7 0

During a call

Put on hold	1 (or R)
Make a second call	1 (or R)
Broker's call	2 (or R + 2)
Conference	Call a 2nd party + 3 (or R+ 3)
Transfer a call to another extension	Dial extension No. (or R + extension No. + (before or after answer)
Call parking	1 (or R) + 1 0 + 2 digits of your choice +
Retrieve a parked call	+ 1 0 + chosen 2 digits code

QUICK REFERENCE GUIDE

Temporary call forwarding +

	ACTIVATION	DEACTIVATION
Immediate call forwarding	6 1 + No. you want to fwd	6 0
Call forwarding on no answer	6 2 + No. you want to fwd	6 0
Call forwarding on busy	6 3 + No. you want to fwd	6 0
Call forwarding on no answer or busy	6 9 + No. you want to fwd	6 0
Do not disturb	6 4	6 0
Follow me	6 5 + Your extension number + password	6 0 from your terminal
Follow me (from another extension)	6 5 + * + Your extension No. + temporary extension No. + password	6 0 from your terminal

Programming your terminal +

	ACTIVATION	DEACTIVATION
Reminder	7 1 + HHMM 4 digits - time of the appointment	7 1 + 9
Temporary operator	6 7	6 7 + password
Retrieve from group	6 8	6 8
Lock your phone	7 8	7 8 + password
Change password	7 9 + old password + new password	

MD Evolution System Telephone

ANALOG PHONES

For questions regarding the product,
please contact your Aastra Certified Sales Partner.
Also visit us on: www.aastra.com

© Aastra Telecom Sweden AB 2008. All rights reserved.
EN/LZTBS 103 024 R2A

Subject to alteration without notice

